



## NURIT 2080/2085 DOWNLOAD INSTRUCTIONS

**\*Make sure there are no transactions in terminal!!!**

---

### NURIT 2080/2085 TERMINAL PROGRAMMING

---

- |  |   |
|--|---|
| 1. <b>Display:</b> SALE >                    | <b>Key:</b> Press Menu/ESC, BATCH, VOID, Enter at the same time.                              |
| 2. <b>Display:</b> 2085 NOS 1. Back to Prog> | <b>Key:</b> Press 2   |
| 3. <b>Display:</b> 2085 NOS 2. Download>     | <b>Key:</b> Press Enter   |
| 4. <b>Display:</b> Swipe Merchant Card...    | <b>Key:</b> Type in Download Serial number and press Enter                                    |
| 5. <b>Display:</b> 1. Auto Load>             | <b>Key:</b> Press 2 then Enter  |
| 6. <b>Display:</b> 2. Comm PRM>              | <b>Key:</b> Press Enter   |
| 7. <b>Display:</b> Phone>                    | <b>Key:</b> Key in phone number, press Enter  |
| 8. <b>Display:</b> Phone>XXXXXXXXXXXX        | <b>Key:</b> Press Forced 2 times  |
| 9. <b>Display:</b> 3. VIA>COM1 or Modem      | <b>Key:</b> If VIA>COM1 Press Enter until it reads VIA>Modem (not ext. Modem), Press Menu/ESC |
| 10. <b>Display:</b> 2. Comm PRM>             | <b>Key:</b> Press Return 1 times  |
| 11. <b>Display:</b> 1. Auto Load             | <b>Key:</b> Press Enter   |

\*Full download requires 30-40 minutes to complete.

---

#### Notes:

Default Password: Date Backwards, for example, today is **01/21/2007**, password is 2101. (FOR NOS 6.XX and Below) Full Date, for example, 01/21/2007, password is 01212007 (NOS 7.XX and above)